

SERVICE MANUAL

R-725/RDS · AV-725 AUDIO/VIDEO PRO-LOGIC RECEIVER



■ CONTENTS ■

SAFETY PRECAUTIONS	1	PRINTED CIRCUIT BOARDS	18
SPECIFICATIONS	2	ELECTRICAL PARTS LIST	26
CIRCUIT DESCRIPTION	5	IC FUNCTIONAL BLOCK DIAGRAM	32
ALIGNMENT PROCEDURES	10	BLOCK DIAGRAM	36
TROUBLESHOOTING	13	WIRING DIAGRAM	38
MECHANICAL PARTS LIST	15	SCHEMATIC DIAGRAMS (I), (II), (III)	40
EXPLODED VIEW	16	SCHEMATIC DIAGRAMS (IV), (V), (VI)	45

* A PRODUCT OF AV-725 OMITS ONLY TUNER PART TO R-725

 **Sherwood®**

SAFETY PRECAUTIONS

WARNING


Before servicing this unit, familiarize yourself with the following precautions:

1. Many electrical and mechanical parts in this chassis have special safety characteristics that often pass unnoticed and the protection afforded by them cannot necessarily be obtained by using replacement components rated for higher voltage, wattage, etc. Replacement parts that have these special safety characteristics are identified in this manual and its supplements: electrical components having such features are identified by ! in the schematic diagram and the parts list.

Before replacing any of these components, read the parts list in this manual carefully. The use of substitute replacement parts that do not have the same safety characteristics as specified in the parts list may create shock, fire, or other hazards.

2. Before returning the set to the customer, always do an AC leakage current check on the

exposed metal parts of the cabinet, such as terminals, screw heads, and metal overlays, to be sure the set is safe to operate danger of electrical shock. Plug the AC line cord directly into a 120 V AC outlet (120 V AC version only). (Do not use a line isolation transformer during this check.) Be sure your AC voltmeter has a sensitivity of 5000 Ω per volt or greater. Then connect a 1500 Ω 10 watt resistor, paralleled by a 0.15 μ F 150 V AC capacitor, between a known good earth ground (such as a water pipe, or conduit) and the exposed metallic is parts, one at a time. Measure the AC voltage across the combination of a 1500 Ω resistor and a 0.15 μ F capacitor. Reverse the AC plug at the AC outlet and repeat AC voltage measurements for each exposed metallic part. Voltage measured must not exceed 0.75V RMS. This corresponds to 0.2 mA AC. Any value exceeding this limit constitutes a potential shock hazard and must be corrected immediately.



SPECIFICATIONS

FRONT AMP SECTION

Measuring methods are based on IHF and IEC standard 268-3.

Measurements conditions, unless otherwise noted :

* Output resistive load : 8 ohms/Both channel driven

* Tone(Bass, Treble), Balance, EQ control : Center Position, Other SW's : OFF.

* Nominal input level : 5 mV for MM, 0.5 mV for MC, 500 mV for general purpose inputs.

* Power figures should be kept minimum 10 min. between 15 and 35 °C.

* Terminator : 100 ohm for MC, 1 kohm for MM and general purpose inputs.

* Filter : IHF-A filter

* R/O : Rated Output

NO	DESCRIPTION	INPUT	FREQ.	REMARK	UNIT	LIMIT	NOMINAL
1	Input Sensitivity	AUX	1 kHz		mV	200 ± 50	200 ± 30
		MM	1 kHz		mV	2.5 ± 0.5	2.5 ± 0.3
2	Channel Balance	AUX	1 kHz	R/O TO -40dB	dB	± 3	± 2
			1 kHz	-40 TO -60dB	dB	± 6	± 4
3	Residual Noise	AUX	1 kHz	VOL min.	mV	≤ 1	≤ 7
4	Total Harmonic Distortion	AUX (500mV)	20Hz	R/O 1W	%	≤ 0.2	≤ 0.09
			1kHz	"	%	≤ 0.2	≤ 0.09
			20Hz	"	%	≤ 0.3	≤ 0.2
5	Continuous Average Power at (0.2)% THD	AUX	20Hz	8 ohms	W	130	132
			1kHz	"	W	130	132
			20Hz	"	W	130	132
6	IMD(SMPTE)	AUX(500mV)	60Hz=4	R/O	%	≤ 0.2	≤ 0.09
			7kHz=1	1W	%	≤ 0.2	≤ 0.09
7	S/N RATIO, IHF-A FILTER	AUX(500mV)	1kHz	R/O	dB	≥ 90	≥ 93
		MM(5mV)	1kHz	R/O	dB	≥ 68	≥ 72
8	Channel Separation	AUX(500mV)	100Hz	R/O -3dB	dB	≥ 45	≥ 55
			1kHz	"	dB	≥ 45	≥ 55
			10kHz	"	dB	≥ 40	≥ 45
9	Function Crosstalk	CD → AUX	1/10 kHz	"	dB	≥ 60/40	≥ 65/45
		AUX → MM	1/10 kHz	"	dB	≥ 60/40	≥ 65/45
		MM → AUX	1/10 kHz	"	dB	≥ 60/40	≥ 65/45
10	Frequency Response (-3dB)	AUX(500mV)		1W	Hz~kHz	20~50	10~60
11	Tone Control, ± 10dB	AUX	100Hz	1W	dB	± 10 ± 2	± 10 ± 1
			10kHz	1W	dB	± 10 ± 2	± 10 ± 1
12	Subwoofer Out sub-vol +6dB	AUX(200mV)	1kHz	M-Vol Max	V	2 ± 0.5	2 ± 0.3
13	Phono Equalization	PHONO	100Hz	TAPE OUT	dB	RIAA ± 1.5	RIAA ± 1
			10kHz	"	dB	RIAA ± 1.5	RIAA ± 1
14	Input Overload at 0.5% THD	MM	1kHz	TAPE OUT	mV	≥ 120	≥ 140
15	DIN Power at 1% THD	AUX	1kHz	R/O	W	≥ 135	≥ 140
16	Muting Level	AUX(500mV)	1kHz	R/O	dB	≥ 60	≥ 65

REAR AMP SECTION

Measurements conditions : Input level 300mV, Rear level max., Master volume adj. delay time 20ms

NO	DESCRIPTION	INPUT	FREQ.	REMARK	UNIT	LIMIT	NOMINAL
1	Power Output 0.7% THD	AUX	1kHz	8ohms	W	≥ 50	≥ 52
2	Total Harmonic Distortion	AUX	1kHz	1W	%	≤ 1	≤ 0.7
3	S/N Ratio DOLBY	AUX		R/O	dB	≥ 55	≥ 63
	IHF-A Filter STADIUM	AUX		"	dB	≥ 55	≥ 63
	THEATER	AUX		"	dB	≥ 55	≥ 63
	HALL	AUX		"	dB	≥ 50	≥ 63
4	Frequency Response at ± 3 dB (ONLY DOLBY)	AUX	1kHz	1W	Hz~kHz	100~6	80~7

☛ CENTER AMP SECTION

Measurements conditions : Input level 300mV, WIDE mode Center level max., Master volume adj.

NO	DESCRIPTION	INPUT	FREQ.	REMARK	UNIT	LIMIT	NOMINAL
1	Power Output at 0.3% THD	AUX	1kHz	8ohms	W	≥ 130	≥ 132
2	Total Harmonic Distortion	AUX	1kHz	1W	%	≤ 0.3	≤ 0.2
3	S/N Ratio, IHF-A Filter	AUX		R/O	dB	≥ 73	≥ 78
4	Frequency Response						
	DOLBY MODE NORMAL	AUX		1W	Hz~kHz	120~20	100~30
	WIDE	AUX		1W	Hz~kHz	60~20	40~30

☛ VIDEO SECTION

NO	DESCRIPTION	INPUT	FREQ.	REMARK	UNIT	LIMIT	NOMINAL
1	Output Level at 75ohms	VCR1(1Vp-p)	1MHz		Vp-p	1 ± 0.2	1 ± 0.1
2	Frequency Response	"	1MHz		Hz~MHz	DC~6	DC~6.3
3	S/N Ratio	"	1MHz		dB	40	45
4	Crosstalk	"	1MHz		dB	40	45

☛ AM SECTION

Measuring methods in conformity with IEC standard 315

Measurements condition AM - MW

* Radio frequency = 1000/999kHz, Audio frequency = 400Hz

* LM : Radio frequency = 207kHz, Audio Frequency = 400Hz

* Reference level = 5 mV/m, 10 mV/m on 50 ohms

* Test point : MW TP1=594 kHz, TP2=999 kHz, TP3=1404 kHz (USA Version)

* Test point : MW TP1=600 kHz, TP2=1000 kHz, TP3=1400 kHz (Europe Version)

* Test point : LW TP1=162 kHz, TP2=207 kHz, TP3=1404 kHz (USA Version)

* Test point : LW TP1=600 kHz, TP2=1000 kHz, TP3=1400 kHz (Europe Version)

NO	DESCRIPTION		VERSION	UNIT	LIMIT	NOMINAL
1	Tuning Cover Range	LOW~HIGH	USA	kHz	520~1710	
	STEP		EUROPE	kHz	522~1611	
			USA	kHz	10	
			EUROPE	kHz	9	
2	Usable Sensitivity	MW TP1	USA	uV/m	≤800	≤500
		TP2		uV/m	≤800	≤500
		TP3		uV/m	≤800	≤500
		MW TP1	EUROPE	uV/m	≤800	≤500
		TP2		uV/m	≤800	≤500
		TP3		uV/m	≤800	≤500
3	S/N Ratio	MW	USA	dB	≥35	≥40
			EUROPE	dB	≥40	≥45
4	Total Harmonic Distortion		USA	%	≤2	≤1.0
			EUROPE	%	≤1.5	≤1.0
5	Over Load Distortion 5 mV 80 % MOD			%	≤10	≤5
6	Frequency Response at - 6 dB	MW		Hz	100~2 K	80~2.2K
7	Selectivity 10 kHz/ 9 kHz	MW		dB	≥20	≥25
8	AGC Figure of Merit			dB	≥50	≥55
9	Image Rejection	MW = TP3		dB	≥30	≥35
10	Whistle Modulation Input=1mV/m 21F			%	≤15	≤10
11	Auto Stop Level	MW		uV/m	800(±6dB)	800(±5dB)
12	Tuned Level	MW		uV/m	800(±6dB)	800(±5dB)
13	Output Level			mV	165±50	165±30

FM SECTION

Measuring methods in conformity with IEC standard 315

Measurements condition FM : Radio frequency = 98.1 MHz, Audio frequency = 1kHz

* Reference level = 1mV on (75 ohms, 300 ohms)

* Deviation : MONO = $\pm 75\text{kHz}$, Stereo = $\pm 67.5\text{kHz} \pm 7.5\text{kHz}$ (USA Version)

MONO = $\pm 40\text{kHz}$, Stereo = $\pm 40\text{kHz} \pm 7.5\text{kHz}$ (Europe Version)

* Test Point : TP 1 = 90.1MHz, TP2 = 98.1MHz, TP 3 = 106.1MHz

* Filter = B.P.F at STEREO

NO	DESCRIPTION		VERSION	UNIT	LIMIT	NOMINAL
1	Tuning Renge	LOW~HIGH	USA	MHz	87.5 ~ 107.9	
	Step	AUTO/Man	Europe USA Europe	kHz	87.5 ~ 108.0 200 100/50	
2	Usable Sensitivity S/N = 30 dB	TP 1	USA	dBf	≤ 17.2	≤ 14.2
		TP 2		dBf	≤ 17.2	≤ 14.2
		TP 3		dBf	≤ 17.2	≤ 14.2
	S/N = 26 dB	TP 1	Europe	dBf	≤ 20.2	≤ 17.2
		TP 2		dBf	≤ 20.2	≤ 17.2
		TP 3		dBf	≤ 20.2	≤ 17.2
3	Full Limiting Sense	Output = -3 dB	USA	dBf	≤ 15.2	≤ 12.2
			Europe	dBf	≤ 20.2	≤ 17.2
4	Auto Stop Level			dBf	31.2±5	31.2±3
5	Auto Error		USA	kHz	±20	±25
			Europe	kHz	±15	±20
6	S/N Ratio	MONO		dB	≥64	≥68
		STEREO		dB	≥60	≥64
7	Total Harmonic Distortion	MONO		%	≤0.5	≤0.3
		STEREO		%	≤0.8	≤0.5
8	50 dB Quietion Sensitivity	MONO	USA	dBf	≤23.2	≤20.2
		STEREO		dBf	≤48.3	≤45.3
	46 dB Quietion Sensitivity	MONO	Europe	dBf	≤23.2	≤20.2
		STEREO		dBf	≤48.3	≤45.3
9	Channel Separation	100 Hz		dB	≥35	≥40
		1 kHz		dB	≥40	≥45
		10 kHz		dB	≥30	≥35
10	Frequency Response at ±1.5 dB			Hz	20~12.5	10~14
11	Spurious Response		USA	dB	≥70	≥80
			Europe	dB	≥80	≥90
12	IF Rejection	TP 1		dB	≥70	≥80
13	Image Rejection	TP 3	USA	dB	≥60	≥65
			Europe	dB	≥70	≥80
14	AM rejection Ratio			dB	≥50	≥55
15	Capture Ratio			dB	≤2.5	≤2
16	Alternative CH Selectivity ±400 kHz			dB	≥45	≥50
17	Output Level	MONO		mV	500±150	500±100
18	RDS Sensitivity		Europe	dBf	≤40.2	≤38.2

GENERAL

Power consumption ----- USA/Canada : 4.5A, Europe : 1 100W

Power Supplies ----- USA/Canada : AC 120V, 60Hz

Europe : AC 230V, 50Hz

Dimensions (W×H×D) ----- 440×140×38 mm


17-5/16×5-1/2×14-15/16 inches

Weight (Net)- ----- 15.9 kg (35.3 lbs)

CIRCUIT DESCRIPTION

IC301 : CXP82840

1. Pin Description



2. Input/Output Terminal Functions

Pin No.	Symbol	Description
1/2	G2/G1	Grid signal output for FIP.
3	NC	Not used.
4	POWER DOWN	Input for power down(Active low).
5	RDS CHECK	Input for RDS check.
6	RDS START	Input for RDS start.
7/9	ENC UP/DOWN	Input for Encoder up and down. <div style="text-align: center;"> <div style="display: inline-block; margin-right: 20px;"> <p>(C W)</p> </div> <div style="display: inline-block;"> <p>(C C W)</p> </div> </div>
8	REMOCON	Input for remote control signal. (Active low).
10/11	NC	Not used.
12	MAIN MUTE	Output for main mute. Output is low level under the following conditions. <ol style="list-style-type: none"> 1. When power is turned on or off. 2. When function is changed. 3. When MONO or STEREO is changed. 4. When Low level is inputted to "PROTECTION" port of CPU. 5. When mute signal is received from the commander.
13	DATA	Output datasignal to MC14094, LC7821, LC7822 and TC9299.
14	CLOCK	Output clock signal to MC14094, LC7821, LC7822 and TC9299.
15	NC	Not used.
16~19	KEY IN1~4	Input data of IN1~IN4 for key scan.
20	DIGI LINK	Input/Output for controlling digi-link .
21	MODEL OPTION	Input for selecting Model. ('L'→R525, 'H'→R-725, AV725)
22	RDS CLK	RDS clock signal input for TDA7330B. (This input is used only for R525RDS)
23	RDS DATA	RDS data signal input for TDA7330B. (This input is used only for R525RDS)
24	C-MUTE	Output for center mute. Output is low level under the following conditions. <ol style="list-style-type: none"> 1. When power is turned on or off. 2. When center mode is on or off. 3. When center mode is switched.

Pin No.	Symbol	Description																
24	C-MUTE	4. When test tone mode is on or off, When the channels is changed the test tone mode. 5. When Low level is inputed to "PROTECTION" of CPU. 6. When mute signal is received from the commander.																
25	S-MUTE	Output for surround mute. Output is low level under the following conditions. 1. When power is turned on or off. 2. When surround mode is on or off. 3. When test tone mode is on or off, When the channels is changed the test tone mode. 4. When delay time is changed. 5. When Low level is inputed to "PROTECTION" of CPU. 6. When mute signal is received from the commander.																
26/27	7001-DATA/CLK	DATA/CLOCK Singnal output for LM7001.																
28	AV REF	Referance voltage of analog A/D converter.																
29	SLEEP OPTION	Input for selecting function. ('H'→St-by, 'L'→Sleep.)																
30	PROTECTION	Signal input for protection wher low level is inputed, it ischinged to STAND-BY mode.																
31	GND	Ground.																
32	STEREO	Input for lighting the ST(Stereo), Inaicator(Active low).																
33	S-METER	Input signal level of tuner.																
34	SUBWOOFER OPTION	Inplut for selecting subwoofer, when high level is inputed subwoofer volume is operates.																
35	STEP	According to region, input for selecting the frequency bands and steps for FM and AM Settings are as follows <table><tr><th>REGION</th><th>FREQUENCY BAND</th><th>STEP</th><th>PIN35(IC301)</th></tr><tr><td>USA/ CANADA</td><td>FM: 87.5 ~ 107.9 MHz AM: 520 ~ 1710 kHz</td><td>200 kHz 10 kHz</td><td>0 V</td></tr><tr><td>EUROPE</td><td>FM: 87.5 ~ 108 MHz AM: 522 ~ 1611 kHz</td><td>50 kHz 9 kHz</td><td>1 V</td></tr><tr><td>KOREA</td><td>FM: 87.5 ~ 107.9 MHz AM: 522 ~ 1611 kHz</td><td>200 kHz 9 kHz</td><td>2 V</td></tr></table>	REGION	FREQUENCY BAND	STEP	PIN35(IC301)	USA/ CANADA	FM: 87.5 ~ 107.9 MHz AM: 520 ~ 1710 kHz	200 kHz 10 kHz	0 V	EUROPE	FM: 87.5 ~ 108 MHz AM: 522 ~ 1611 kHz	50 kHz 9 kHz	1 V	KOREA	FM: 87.5 ~ 107.9 MHz AM: 522 ~ 1611 kHz	200 kHz 9 kHz	2 V
REGION	FREQUENCY BAND	STEP	PIN35(IC301)															
USA/ CANADA	FM: 87.5 ~ 107.9 MHz AM: 520 ~ 1710 kHz	200 kHz 10 kHz	0 V															
EUROPE	FM: 87.5 ~ 108 MHz AM: 522 ~ 1611 kHz	50 kHz 9 kHz	1 V															
KOREA	FM: 87.5 ~ 107.9 MHz AM: 522 ~ 1611 kHz	200 kHz 9 kHz	2 V															
36	SET OPTION	Input for selecting set. (5V→RDS Receiver, 2.5V→Amp, 0V→Receiver)																
37	ADGND	Ground																
38	RESET	Input for resetting CPU. (Active high)																
39/40	X-TAL I/O	Input/Output for cystal oscillator.																
41	GND	Ground.																

Pin No.	Symbol	Description
42	NC	Not used.
43	GND	Ground.
44	VDD	Power supply of CPU(+5V).
45	VFL	-30V Power supply for FIP.
46/47	VOL UP/DOWN	Output data for Master volume control.
48	VOL LED	Output signal for volume LED.
49	CE(7822)	LC7822 chip enable (Surround).
50	CE(4094)	14094 chip enable (Surround).
51	CE(4094)	14094 chip enable (Video).
52	CINEMA-BASS	Output signal for Cinema-Bass function (High Active).
53	NC	Not used.
54	AMP-MUTE	When the power is on, control data output is high after 3 seconds. When the power is off, control data output is "L".
55	VCR2 OPTION	Output signal for VCR2 Inputs. ('H'-Front, 'L'-Rear)
56	CE(7001)	LM7001 chip enable.
57	CE(9299)	TC9299 chip enable. (Surr-Subwoofer Trim)
58	CE(7821)	LC7821 chip enable. (Function select)
59	T-MUTE	Output for tuner mute. Output is high level under the following conditions. 1. When power is turned on or off. 2. When tuner band is changed. 3. When tuning up or down button is pressed. 4. When preset button is pressed. 5. When displayed preset number is changed during memory scan. 6. When Low lever is inputed to "PROTECTION" of CPU. 7. When mute signal is received from the commander.
60	NC	Not used.
61	ST-BY	Output for driving power relay. (Active high)
62-70	S1-S9	Segment 1 - Segment 9.
71-81	S10-S20	Segment 10, Key check 11 - Segment 20, Key check 1.
82-88	S21-S27	Segment 21 - Segment 27.
89	VDD	+5V power supply.
90-94	S28 - S32	Segment 28 - Segment 32.
95-100	G8-G3	Grid 1 - Grid 5.

ALIGNMENT PROCEDURES

TUNER


1. Equipment Required

- AM Standard Signal Generator (AM SSG)
- Oscilloscope
- AC Voltmeter
- FM Standard Signal Generator (FM SSG)
- Stereo Modulator
- Audio Generator
- Distortion Meter
- DC Voltmeter
- Frequency Counter

Note : Disconnect external FM antenna prior to alignment.

2. Alignment

2-1. Alignment and Test Point



2-2. AM Alignment

- Output of signal generator should not be greater than necessary to obtain an optimum output reading.
- Signal generator modulation : 30 %
- RF signal frequency : 400 Hz
- Switch : Press the BAND button to AM

Step	Subject	Signal Generator Frequency	Set Frequency Setting	Equipment Connection	Adjustment Point	Adjust for
1	Tuning Voltage	520kHz (522kHz)	520kHz 1) (522kHz)	DC Volt meter to J22 (TP1)	T2 AM OSC(R)	DC1.32V±1.35V
2	RF Tuning	600kHz (594kHz)	600kHz 1) (594kHz)	AC voltmeter and oscilloscope to speaker terminal of L or R channel	T1 MW ANT(W)	Maximize audio output
		1400kHz (1404kHz)	1400kHz 2) (1404kHz)		TC1	
* Feed signal should be fed to loop antenna through the test loop antenna 60 cm distant from the appliance. * Repeat the step 1) and 2) until no further improvement occurs.						

3	IF	1000kHz (999kHz)	1000kHz (999kHz)	Ac voltmeter and oscilloscope to speaker terminal of L or R channel	T3 AM IFT	Maximize audio output
4	Tuned Level	1000kHz (999kHz) 800 μ V/m	1000kHz (999kHz)		VR1	"Tuned" flag in the FL display light on

3-3. FM Alignment

- Output of signal generator should not be greater than necessary to obtain an optimum output reading.
- Signal generator deviation : USA/Canada/Korea : 75kHz. Europe : 40kHz
- RF signal frequency : 1 kHz
- Switch : Press the BAND button to FM and the FM MODE button to MONO

Step	Subject	Signal Generator Frequency	Set Frequency Setting	Equipment Connection	Adjustment Point	Adjust for
1	Tuning Band Width	98.1MHz (98MHz)	98.1MHz (98MHz)	DC Volt meter to R26(PCB1)	T4	Zero reading on DC Volt meter
2	THD	98.1MHz (98MHz)	98.1MHz (98MHz)	Distortion meter to TAPE OUT jack of L or R channel	T5	Minimize distortion
3	Tuned Level	98.1MHz (98MHz) SSG output level : 10 μ V/m	98.1MHz (98MHz)		VR2	"Tuned" flag in the FL display light on

3-4. MPX Alignment


- Signal generator frequency : 98 MHz
- Signal generator deviation : USA : 75kHz. Europe : 40kHz
- RF signal frequency : 1 kHz
- Signal generator output level : 1000 μ V/m
- Connect signal generator to FM antenna terminal through FM dummy antenna (75 Ω)
- Switch : Press the BAND button to FM and the FM MODE button to STEREO

Step	Subject	19 kHz Modulation Level	Signal Generator Setting	Equipment Connection	Adjustment Point	Adjust for
1	Seperation R \rightarrow L	8 % Modulation	Pilot on	AC voltmeter to speaker terminal of R channel	VR3	Set AC voltmeter to 0 dB
				AC voltmeter to speaker terminal of L channel		AC voltmeter reading should be at least 40 dB below
2	Seperation L \rightarrow R	8 % Modulation	Pilot on	AC voltmeter to speaker terminal of L channel	VR3	Set AC voltmeter to 0 dB
				AC voltmeter to speaker terminal of R channel		AC voltmeter reading should be at least 40 dB below


If you could not obtain -40 dB readings in steps 1 and 2, readjust VR3 until you obtain -40 dB readings.
Nominal is -45 dB. (Europe: Nominal -42 dB, Limit -37 dB)

4. Equipment Connection

4-1. AM Alignment Connection




4-2. FM Dummy Antenna



FM Dummy Antenna to 300Ω Antenna terminal of system.

4-3. FM RF/IF and MPX Alignment Connection



TROUBLESHOOTING

Symptom	Cause and Remedy
Receiver inoperative. (FL indicator does not light.)	A) Faulty AC power cord. Replace. B) Defective the power switch. Replace. C) Broken wire in the power transformer. Replace. D) Blown fuse. Replace the fuse.
Fuse blows when power is turned on.	A) Defective power transformer. Replace. B) Short on the primary or secondary of the transformer circuitry. Repair the short. C) Damaged rectifier D105-D112 or damaged transistor Q215L/R/C/SL, Q216L/R/C/SL. D) Short circuit in the amplifier circuit. Repair the shorted component(s) in the amplifier circuit.
Power indicator lights but no sound from both channels.	A) Defective in transistor Q215L/R, Q216L/R on the AMP302 Board. B) Pulled out of correct speaker switch.
One channel does not work when volume is at maximum with a test signal applied to the center terminal of volume control of the dead channel.	A) Defective in transistor Q215L/R or Q216L/R on the AMP302 Board. Replace the defect. B) Break in copper foil of printed circuit board. Repair the defect. C) Short in speaker output terminal. Repair or replace.
Speaker works normally but headphones inoperative.	A) Headphone plug does not match with jack. Replace the jack. B) Defective resistor R701L/R. Replace.
FM inoperative	A) Defective front-end (FE). Replace. B) Defective FM switch. Replace the switch. C) Defective transistor Q3 and ICS (IC2, IC3). Replace the defective transistor or IC(s). D) Defective coil T4, T5. Replace the coil(s). E) Defective lead-in. Repair or replace the lead-in. F) Ceramic filters CF1, CF3 defective. Replace the defective ceramic filter(s).
Poor multiplex separation.	A) Improper adjustment. Readjust VR3. B) IC3 defective. Replace. C) Variable resistor VR3 defective. Replace the variable resistor.
FM volume is insufficient.	A) If volume from both L and R channels is not loud enough : Front end section defective. Faulty IC2, Coil T4 or T5. If sound of one channel is not loud enough : Defective VR3.

Symptom	Cause and Remedy
STEREO indicator does not light.	A) Defective indicator in FL. Replace. B) Improper adjustment of VR2 of tuner board. Make readjustment. C) Defective IC2. Replace the defective component.
FM Mono has no effect.	A) Defective FM MODE switch. Replace.
AM inoperative.	A) Damaged IC2 of tuner Board. Replace. B) Defective T1, T2, T3 or CF4 of Tuner Board. Replace the defective component(s). D) Defective varicap diodes VD1 or VD2. Replace varicap diodes(s). E) Damaged AM loop antenna. Repair or replace.
Bass control has no effect.	A) Variable resistor BASS defective. Replace.
Treble control has no effect.	A) Variable resistor TREBLE defective.
Auto tune inoperative. (UP/DOWN)	A) Poor contact in Up/Down key. Repair or replace. B) Defective IC301. Replace. C) Defective tuner Circuit components. Replace. D) In case of FM only, improper adjustment of FM front-end. Readjust.
Manual tune inoperative. (UP/DOWN) (AM or FM)	A) Poor contact in Up/Down key. B) Defective IC301. Replace.
Memory setting inoperative.	A) Poor contact in memory keys 1-10. Replace the defective component. B) Defective IC301. Replace the defective component.
FL inoperative.	A) FL defective. Replace. B) Defective IC301. Replace. C) Defective X-TAL 301. Replace.
Noisy volume control.	A) Defective volume. Replace.
Remote Control Unit inoperative.	A) Weak battery. Replace. B) Defective. Replace. C) Defective IC301 (FRONT Board) Replace.

MECHANICAL PARTS LIST

Ref. No	Description	Part No.	Q'ty	Version	Ref. No	Description	Part No.	Q'ty	Version
	PACKAGE				56	HOLDER PCB	4320044751010	1	
	BOX CARTON	6017040990160	1	D/RDS	57	TERMINAL SPEAKER, 4P	G61204030000B	1	
	BOX CARTON	6017040990190	1	A	58	TERMINAL SPEAKER, 2P	G611040310000	1	
	POLY BAG	6330040092010	1		59	TERMINAL SPEAKER, 8P	G614081036000	1	
	FILM SOFT PE	6320040052010	1		60	BUSHING TERMINAL	2410040270010	14	D/RDS
	CUSHION PLOY	6230042794010	1		61	GROUND TERMINAL	3790000090000	1	
	ACCESSORIES				62	CHASSIS BACK	3207042746010	1	K
	ANTENNA WIRE DIPOLE	E605010010000	1		(62)	CHASSIS BACK	3207042746020	1	A
	ANTENNA LOOP	E601010000000	1		(62)	CHASSIS BACK	3207053166010	1	D
	MATCHING TRANS	L109284007100	1		(62)	CHASSIS BACK	3207042746050	1	RDS
	COMMANDER ASSY	830004025X010	1		63	STOPPER CORD	4380040162010	1	
	BATTERY 1.5V AA (R6M)	G670001R50010	2		64	CORD AC POWER	L061041210010	1	A
	MANUAL INSTRUCTION	5707045950010	1	D/RDS	65	CORD AC POWER	L061040421040	1	D/RDS
	MANUAL INSTRUCTION	5707046390010	1	K	(65)	CORD AC POWER	L061041220010	1	K
	MANUAL INSTRUCTION	5707046390030	1	A	66	COVER TOP	3000045396010	1	A/K
	CABINET & CHASSIS				(66)	COVER TOP	3000045406050	1	D/RDS
1	PANEL FRONT	3067043468050	1	A/K	67	BRACKET PCB	4010056216010	1	
(1)	PANEL FRONT	3067046128010	1	D	68	JACK PHONE (G)	G402040161330	1	
(1)	PANEL FRONT	3067046138010	1	RDS	69	HOLDER FAN	4320044706010	1	
2	KNOB MAIN	5087040768010	1		70	DC-BRUSHLESS FAN	G720040030020	1	
3	KNOB ENCODER	5087040778010	1		71	CLAMPE WIRE	4330040213010	2	
4	KNOB ROTARY(A)	5097050641010	3		72	FELT BUFFER	4050045669010	1	A/K
5	BADGE, Sherwood	5637040591010	1		SW1	SWITCH POWER	G000041610000	1	D/RDS
6	LED GUIDE	4350041551010	1		SW2/SW3	SWITCH PUSH	G000041170000	2	
7	CAP DECORATION	5127040931010	1	A/K	SW4	SWITCH TACT	G180040500010	1	A/K
(7)	CAP DECORATION	5127040931020	1	D/RDS	SW5-SW21	SWITCH TACT	G180040500010	17	
8	WINDOW FL	5077040063010	1	A/K	SW22-SW26	SWITCH TACT	G180040500010	5	RDS
(8)	WINDOW FL	5077040073010	1	D/RDS	SW27	SWITCH TACT	G180040500010	1	A/K
9	BODY FRONT	3417040721010	1	A/K	SW28-SW43	SWITCH TACT	G180040500010	16	
(9)	BODY FRONT	3417040721020	1	D	VR1	VOULME MAIN	C495145300010	1	
(9)	BODY FRONT	3417040731010	1	RDS	VR2	VOULME BLANCE	C450042050000	1	
10	JACK RCA, 3P	G6060403000000	1		VR3/VR4	VOULME BASS/TREBLE	C450042060000	2	
11	BRACKET JACK SWITCH	4010043616010	1		VR5	VOULME ENCODER	C450042030010	1	
12	BUTTON PUSH	5090066821010	2			HARDWARE KIT			
13	INDICATOR STANDBY	5160040643010	1		S1/S2	SCREW #2FTC 3×8B	B010530083F10	2	
14	BUTTON STANDBY	5090059231010	1		S3-S55	SCREW #BTT 3×8B	B020030083B10	53	
15	BUTTON POWER	5090059071010	1	A/K	S56-S69	SCREW #B WPTT 3×6Y	B020030061W10	14	
16	BUTTON POWER	509005399101A	1	D/RDS	S70-S79	SCREW #2 BTT 3×8B	B020030083B10	10	
17	HOLDER FL	4320040841010	2		S80-S104	SCREW HEATSINK	1507041146010	25	
18	SHIELD FENCE	3070046576010	1		S105	SCREW GUIDE(A)	1507041456010	1	
19	CHASSIS FRONT	3210041046010	1		S106/S107	SCREW GUIDE(B)	1507041446010	2	
20	COVER BOTTOM	4310041996020	1		S108-S112	SCREW #B BTT 3×8B	B020030083B10	5	
21/22	FOOT AL	4007041021010	2		S113	SCREW GROUND	1507040996010	1	
23/24	FOOT PL	4000040201010	2		S114-S131	SCREW #B BTT 3×8B	B020030083B10	18	
25	FRAME RIGHT	3200047716010	1		S132	SCREW GROUND	1507040996010	1	
26	CUSHION FL B'D	4050042265010	2		S133-S140	SCREW #B BTT 3×8B	B020030083B10	8	
27/28	HEATSINK, REG TR	2120044338010	2		S141-S144	SCREW GROUND	1507040996010	4	
29	HEATSINK, REG TR	2120044358010	1		S145-S148	SCREW WSAM 4×8B	B020940083W10	4	
30-36	HEATSINK, REG TR	2120044338010	7		S149-S154	SCREW BSAM 4×8B	B020940083B10	6	
37	FASTENER	4420040323010	2		S155-S157	SCREW #B BTT 3×8B	B020030083B10	3	
38	SUPPORTER PCB	4420010153010	2			MISCELLANEOUS			
39	HEATSINK POWER	2120044958010	1			POWER TRANS, 230/50	8200281016870	1	D/RDS
40	FRME LEFT	3200047706010	1			POWER TRANS, 120/60	8200281012670	1	A
41	INSULATION COVER	1240043892010	1			POWER TRANS, 220/60	8200281012770	1	K
42	AC OUTLET	G435040070000	1	A		SPONGE RUBBER	4050045095010	1	
43	AC OUTLET	G435040110000	1	D/RDS		CARD CABLE	L301186213590	1	
(43)	AC OUTLET	G435000160010	1	K					
44	JACK MULTI ROOM	G402042070000	1	A					
45	JACK RCA, 3P	G606300395020	1						
46	JACK RCA, 2P	G601200900020	1	A/D/RDS					
(46)	JACK RCA, 3P	G606300390020	1	K					
47	JACK RCA, 3P	G606300390020	1						
48	JACK RCA, 9P	G607901500010	1						
49	JACK RCA, 4P	G602400910010	1						
50	JACK RCA, 6P	G603600920020	1						
51	JACK RCA, 2P	G601200440020	1						
52	JACK RCA, 6P	G603600920040	1						
53	JACK RCA, 6P	G603600920020	1						
54	ANTENNA TERMINAL	G590040470000	1	A/K					
(54)	ANTENNA TERMINAL	G59004046000A	1	D/RDS					
55	JUMPER PLUG	L063040750000	5						


* Parts with blank version are available in common.

PRODUCT SAFETY NOTICE

Each precaution in this manual should be followed during servicing. Components identified with the IEC symbol Δ in the parts list are of special significance to safety. When replacing a component identified with Δ , use only the replacement parts designated, or parts with the same ratings of resistance, wattage or voltage that are designated in the parts list in this manual. Leakage-current or resistance measurements must be made to determine that exposed parts are acceptably insulated from the supply circuit before returning the product to the customer.


EXPLODED VIEW

Model No. : R-725/RDS · AV-725




Model No. : R-725/RDS · AV-725



PCB2 (MAIN)





PCB4 (AMP 202)




PCB3 (AMP 302)

**CNT-2 B'D**


PCB12 (SURROUND)




PCB1 (TUNER)



PCB10 (SUPPLY)



PCB11 (PRE IN/OUT)



ELECTRICAL PARTS LIST

Ref. No.	Description	Part No.	Q'ty	Version	Ref. No.	Description	Part No.	Q'ty	Version	Ref. No.	Description	Part No.	Q'ty	Version	Ref. No.	Description	Part No.	Q'ty	Version	
PCB1	ASSEMBLY P.C.BOARD TUNER (NON RDS VERSION)				R32	CARBON FILM	5.6 kohm	1/5 W	J C00005628P520	1					C134	CERAMIC TUBULAR	0.1 μF	50 V	K D005103077530	1
	CAPACITORS				R33	METAL FILM	3.3 kohm	1/5 W	J C08003326P520	1					C135-C140	CERAMIC TUBULAR	100 pF	50 V	J D001101077530	6
C1	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1										C141	ELECTROLYTIC SG	1 μF	50 V	M D040010087050	1
C2	CERAMIC DISC	0.047 μF	50 V	Z D004473097060	1	R34	METAL FILM	100 ohm	1/5 W	J C08001016P520	1				C142	CERAMIC TUBULAR	0.01 μF	18 V	D005103773530	1
C3	ELECTROLYTIC SG	3.3 μF	50 V	M D0403R3087100	1	R39	METAL FILM	100 ohm	1/5 W	J C08001016P520	1				C143/C144	ELECTROLYTIC SG	47 μF	25 V	M D040470084100	2
C4	CERAMIC TUBULAR	0.01 μF	16 V	D005103773530	1	R40	CARBON FILM	47 kohm	1/5 W	J C00004738P520	1				C145/L/R	CERAMIC TUBULAR	100 pF	50 V	J D001101077530	2
C5	ELECTROLYTIC SG	47 μF	16 V	M D040470083100	1	R42	METAL FILM	3.3 kohm	1/5 W	J C08003326P520	1				C146	ELECTROLYTIC SG	470 μF	10 V	M D040471082100	1
C6	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1	R43	CARBON FILM	22 kohm	1/5 W	J C00002236P520	1				C147	CERAMIC TUBULAR	0.1 μF	50 V	K D005103077530	1
C7	CERAMIC TUBULAR	0.01 μF	16 V	D005103773530	1	R44	CARBON FILM	47 kohm	1/5 W	J C00004738P520	1				C148/L/R	ELECTROLYTIC SG	10 μF	50 V	M D040100087050	2
C8	CERAMIC DISC CH	18 pF	50 V	J D000180167070	1	R46/L/R	CARBON FILM	220 kohm	1/5 W	J C00002246P520	2				C149	ELECTROLYTIC SG	10 μF	50 V	M D040100087050	1
C9	CERAMIC DISC CH	18 pF	50 V	J D000180167070	1	R47/L/R	CARBON FILM	270 kohm	1/5 W	J C00002748P520	2				C150	ELECTROLYTIC SG	47 μF	25 V	M D040470084100	1
C10	CERAMIC DISC	100 pF	50 V	J D004101067060	1	R48/L/R	METAL FILM	2.7 kohm	1/5 W	J C08002726P520	2				C151	ELECTROLYTIC SG	33 μF	25 V	M D040330084100	1
C11	ELECTROLYTIC SG	47 μF	16 V	M D040470083100	1	R49/L/R	METAL FILM	3.3 kohm	1/5 W	J C08003326P520	2				C152	ELECTROLYTIC SG	470 μF	10 V	M D040471082100	1
C12	CERAMIC DISC	0.022 μF	50 V	Z D004223097060	1										C153/C154	ELECTROLYTIC SG	33 μF	25 V	M D040330084100	2
C13	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1	T1	COILS			D304564300000	1				C155	ELECTROLYTIC SG	470 μF	10 V	M D040471082100	1
C14	ELECTROLYTIC SG	100 μF	16 V	M D040101083100	1	T2	AM-ANT			D940111027000	1				C156/C157	ELECTROLYTIC SG	33 μF	25 V	M D040330084100	2
C15	POLY	470 pF	50 V	J D022471067050	1	T3	AM-OSC			D950010050000	1				C158	ELECTROLYTIC SG	47 μF	25 V	M D040470084100	1
C16	CERAMIC DISC CH	15 pF	50 V	J D000150167070	1	T4	AM-IPT			D970010040000	1				C159	ELECTROLYTIC SG	100 μF	16 V	M D040101083100	1
C17/C18	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	2	T5	FM-DET-A			D970010080000	1				C160/C161	CERAMIC TUBULAR	0.1 μF	50 V	K D005103077530	2
C20	ELECTROLYTIC SG	10 μF	35 V	M D040100085100	1	T6	FM-DET-B			E401500100000	1				C162	ELECTROLYTIC SG	1 μF	50 V	M D040010087050	1
C21/C22	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	2	T6L/R	MPX(19/38KHz)			E401500100000	2				C163/C164	ELECTROLYTIC SG	10 μF	50 V	M D040100087050	2
C23	CERAMIC TUBULAR	0.01 μF	16 V	D005103773530	1										C165	CERAMIC TUBULAR	0.1 μF	50 V	K D005103077530	1
C24/C25	CERAMIC DISC	0.022 μF	50 V	Z D004223097060	2	VR1	SEMI FIXED VARIABLE RESISTORS			C541502115000	1				C166	ELECTROLYTIC SG	1 μF	50 V	M D040010087050	1
C26	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1	VR2	50K(B)-H			C541503115000	1				C167	ELECTROLYTIC SG	1000 μF	35 V	M D040102085200	1
C27	ELECTROLYTIC SG	3.3 μF	50 V	M D0403R3087100	1	VR3	200K(B)-H			C541204115000	1				C168	ELECTROLYTIC SG	1000 μF	35 V	M D040102085200	1
C28	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1										C189-C171	MYLAR	0.047 μF	100 V	J D02047306C060	3
C29	CERAMIC DISC	0.022 μF	50 V	Z D004223097060	1										C172/C173	ELECTROLYTIC SG	15000 μF	80 V	M D04015308B362	2
C30	MYLAR	0.022 μF	100 V	J D02022306C060	1	CN100	MISCELLANEOUS			L112524191000	1				C174-C183	MYLAR	0.1 μF	250 V	K D02010407H080	10
C31	MYLAR	0.0033 μF	100 V	J D02033206C060	1	TC1	PLUG, 15P			D110100901100	1				C184/L/R	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1
C32	MYLAR	0.039 μF	100 V	J D02039306C060	1	X1	CAPACITOR TRIMMER, 10 pF			D110100901100	1				C185/L/R	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	2
C33	ELECTROLYTIC SG	1 μF	50 V	M D040010087050	1	X2	X-TAL, 7.2MHz			E800720000090	1				C186/C187	ELECTROLYTIC SG	47 μF	25 V	M D040470084100	1
C34	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1	X1	CRYSTAL, CSB456F			E830456000050	1				C501/C502	ELECTROLYTIC SG	47 μF	16 V	M D040470083100	2
C35	ELECTROLYTIC SG	100 μF	16 V	M D040101083100	1	FE1	FM TUNER, FTA4-556HB			E900455600100	1				C503/C504	CERAMIC TUBULAR	47 pF	50 V	J D001470067530	2
C36	CERAMIC DISC	330 pF	50 V	J D004331067060	1										C505	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1
C37C	CERAMIC TUBULAR	82 pF	50 V	J D001820077530	1	PCB1	ASSEMBLY P.C.BOARD TUNER (RDS VERSION)								C506/C507	ELECTROLYTIC SG	47 μF	25 V	M D040470084100	2
C38C	CERAMIC TUBULAR	100 pF	50 V	J D001101077530	1		CAPACITORS								C508	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1
C39	ELECTROLYTIC SG	10 μF	35 V	M D040100085100	1	C1	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1				C509-C511	CERAMIC TUBULAR	100 pF	50 V	J D001101077530	3
C41	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1	C2	CERAMIC DISC	0.047 μF	50 V	Z D004473097060	1				C512/C513	ELECTROLYTIC SG	47 μF	25 V	M D040470084100	1
C42	CERAMIC TUBULAR	0.047 μF	50 V	D005473097530	1	C3	ELECTROLYTIC SG	3.3 μF	50 V	M D0403R3087100	1				C514	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1
C43	CERAMIC DISC	680 pF	50 V	J D004681067060	1	C4	CERAMIC TUBULAR	0.01 μF	16 V	D005103773530	1				C515/C516	ELECTROLYTIC SG	47 μF	25 V	M D040470084100	2
C44	ELECTROLYTIC SG	100 μF	16 V	M D040101083100	1	C5	ELECTROLYTIC SG	47 μF	16 V	M D040470083100	1				C518	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1
C45	ELECTROLYTIC SG	1 μF	50 V	M D040010087050	1	C6	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1				C519/C520	CERAMIC TUBULAR	0.001 μF	50 V	K D005102077530	2
C46	ELECTROLYTIC SG	0.22 μF	50 V	M D040R22087100	1	C7	CERAMIC TUBULAR	0.01 μF	16 V	D005103773530	1									
C47	ELECTROLYTIC SG	1 μF	50 V	M D040010087050	1	C8/C9	CERAMIC DISC CH	18 pF	50 V	J D000180167070	2									
C48	CERAMIC DISC	0.022 μF	50 V	Z D004223097060	1	C10	CERAMIC DISC	100 pF	50 V	J D004101067060	1									
C49	ELECTROLYTIC SG	10 μF	35 V	M D040100085100	1	C11	ELECTROLYTIC SG	47 μF	16 V	M D046470083100	1									
C50/L/R	CERAMIC DISC	220 pF	50 V	J D004221067060	2	C12	CERAMIC DISC	0.022 μF	50 V	Z D004223097060	1									
C51/L/R	ELECTROLYTIC SG	10 μF	35 V	M D040100085100	2	C13	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1									
C53	ELECTROLYTIC SG	10 μF	35 V	M D040100085100	1	C14	ELECTROLYTIC SG	100 μF	16 V	M D040101083100	1									
					C15	POLY	470 pF	50 V	J D022471067050	1										
					C16	CERAMIC DISC CH	15 pF	50 V	J D000150167070	1										
CF1	CERAMIC FILTERS				C17/C18	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1										
CF3	10.7MS3GH	E430107000150	1		C20	ELECTROLYTIC SG	10 μF	35 V	M D040100085100	1										
CF4	CFM2-450BL	E431450000120	1		C21/C22	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	2										
					C23	CERAMIC TUBULAR	0.01 μF	16 V	D005103773530	1										
	DIODES				C24/C25	CERAMIC DISC	0.022 μF	50 V	Z D004223097060	2										
D1	ZENER, UZ 5.1V BSB	K06005R114520	1		C26	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1										
D2	1N4148, SWITCHING	K000414801520	1		C27	ELECTROLYTIC SG	3.3 μF	50 V	M D0403R3087100	1										
D5	1N4148, SWITCHING	K000414801520	1		C28	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1										
VD1/VD2	VARACTOR, SVC321 SPA-C	K080032100520	2		C29	CERAMIC DISC	0.022 μF	50 V	Z D004223097060	1										
					C30	MYLAR	0.022 μF	100 V	J D02022306C060	1										
	INTEGRATED CIRCUITS				C31	MYLAR	0.0033 μF	100 V	J D02033206C060	1										
IC1	LM7001M	J124700100010	1		C32	MYLAR	0.039 μF	100 V	J D02039306C060	1										
IC2	LA1268G	J124126600010	1		C33	ELECTROLYTIC SG	1 μF	50 V	M D040010087050	1										
IC3	LA3401	J124340100010	1		C34	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1										
					C35	ELECTROLYTIC SG	100 μF	16 V	M D040101083100	1										
	TRANSISTORS				C36	CERAMIC DISC	330 pF	50 V	J D004331067060	1										
Q1/Q2	2SC1740S, NPN	J5021740S0010	2		C37C	CERAMIC DISC CH	82 pF	50 V	J D000820067060	1										
Q3	KTC1923Y/BKTC3194Y, NPN	J5023194Y0050	1		C38C	CERAMIC DISC	100 pF	50 V	J D004101067060	1										
Q4-Q6	KRA107MDTA114YS, PNP	J601107M00050	3		C39	ELECTROLYTIC SG	10 μF	35 V	M D040100085100	1										
Q8/L/R	DTG323TS, NPN	J602323TS0050	2		C40D	CERAMIC TUBULAR	0.022 μF	25 V	D005223574530	1										
Q9	KRA107MDTA114YS, PNP	J601107M00050	1		C41	ELECTROLYTIC SG	4.7 μF	50 V	M D0404R7087100	1										

Ref. No.	Description	Part No.	Q'ty	Version	Ref. No.	Description	Part No.	Q'ty	Version
R117L/R	METAL FILM	470 ohm 1/5 W J C06004716P520	2		R206C/L/R	METAL FILM	390 ohm 1/5 W J C06003916P520	3	
R118L/R	METAL FILM	470 ohm 1/5 W J C06004716P520	2		R207C/L/R	METAL FILM	390 ohm 1/5 W J C06003916P520	3	
R119L/R	METAL FILM	470 ohm 1/5 W J C06004716P520	2		R208C/L/R	METAL FILM	1.5 kohm 1/5 W J C06001526P520	3	
R120L/R	METAL FILM	470 ohm 1/5 W J C06004716P520	2		R209C/L/R	METAL FILM	1.5 kohm 1/5 W J C06001526P520	3	
R122-R127	METAL FILM	1 kohm 1/5 W J C06001026P520	6		R210C/L/R	METAL FILM	560 ohm 1/5 W J C06005616P520	3	
R128	CARBON FILM	100 kohm 1/5 W J C00001046P520	1		R211C/L/R	METAL FILM	560 ohm 1/5 W J C06005616P520	3	
R129/R130	METAL FILM	220 ohm 1/5 W J C06002216P520	2		R212C/L/R	METAL FILM	560 ohm 1/5 W J C06005616P520	3	
R131	METAL FILM	470 ohm 1/5 W J C06004716P520	2		R213C/L/R	METAL FILM	560 ohm 1/5 W J C06005616P520	3	
R133	METAL FILM	3.3 ohm 1/5 W J C0603R306P520	1		R214C/L/R	METAL FILM	560 ohm 1/5 W J C06005616P520	3	
R134~R137	METAL FILM	3.3 kohm 1/5 W J C06003326P520	4		R215C/L/R	METAL FILM	4.7 kohm 1/5 W J C06004726P520	3	
R138~R140	METAL FILM	75 ohm 1/5 W J C06007506P520	3		R216C/L/R	METAL FILM	560 ohm 1/5 W J C06005616P520	3	
R141-R143	METAL FILM	75 ohm 1/5 W J C06007506P520	3		R217C/L/R	METAL FILM	82 ohm 1/5 W J C06008206P520	3	
R144-R146	METAL FILM	100 ohm 1/5 W J C06001016P520	3		R218C/L/R	METAL FILM	82 ohm 1/5 W J C06008206P520	3	
R147	METAL FILM	75 ohm 1/5 W J C06007506P520	1		R219C/L/R	METAL FILM	1.2 kohm 1/5 W J C06001226P520	3	
R148	METAL FILM	100 ohm 1/5 W J C06001016P520	1		R220C/L/R	METAL FILM	910 ohm 1/5 W J C06009116P520	3	
R154	METAL FILM	10 ohm 2 W J C060010066520	1		R221C/L/R	METAL FILM	1 kohm 1/5 W J C06001026P520	3	
R155	METAL FILM	4.7 ohm 2 W J C0604R7066520	1		R222C/L/R	CARBON FILM	22 kohm 1/5 W J C00002236P520	3	
R156	METAL FILM	10 ohm 2 W J C060010066520	1		R223C/L/R	CARBON FILM	22 kohm 1/5 W J C00002236P520	3	
R157	METAL FILM	470 ohm 1/5 W J C06004716P520	1	A(Only)	R224C/L/R	METAL FILM	82 ohm 1/5 W J C06008206P520	3	
R158L/R	CARBON FILM	100 kohm 1/5 W J C00001046P520	2		R227C/L/R	CEMENT (Dual)	0.27 ohm 5 W J C141R27079300	3	
R159L/R	CARBON FILM	100 kohm 1/5 W J C00001046P520	2		R228C/L/R	METAL FILM	2.2 kohm 1/5 W J C06002226P520	3	
R160/R161	METAL FILM	220 ohm 1/5 W J C06002216P520	2		R229C/L/R	METAL FILM	2.2 kohm 1/5 W J C06002226P520	3	
R188	METAL FILM	4.7 kohm 1/5 W J C06004726P520	1		R230C/L/R	METAL FILM	1 kohm 1/5 W J C06001026P520	3	
R501	CARBON FILM	100 kohm 1/5 W J C00001046P520	1		R231C/L/R	CARBON FILM	5 kohm 1/5 W J C00006826P520	3	
R502	METAL FILM	1 kohm 1/5 W J C06001026P520	1		R232	CARBON FILM	68 kohm 1/5 W J C00006836P520	1	
R503	METAL FILM	1.2 kohm 1/5 W J C06001226P520	1		R233	CARBON FILM	100 kohm 1/5 W J C00001046P520	1	
R504	CARBON FILM	100 kohm 1/5 W J C00001046P520	1		R234	METAL FILM	3.3 kohm 1/5 W J C06003326P520	1	
R505	METAL FILM	1 kohm 1/5 W J C06001026P520	1		R235L/R	METAL FILM	10 ohm 1 W J C060010065520	2	
R506	METAL FILM	1.2 kohm 1/5 W J C06001226P520	1		R237L/R	METAL FILM	10 ohm 1 W J C060010065520	2	
R507/R508	METAL FILM	220 ohm 1/5 W J C06002216P520	2		R238C/L/R	CARBON FILM	22 kohm 1/5 W J C00002236P520	3	
R509/R510	CARBON FILM	100 kohm 1/5 W J C00001046P520	2		R239	METAL FILM	1.5 kohm 1/5 W J C06001526P520	1	
R511~R515	METAL FILM	1 kohm 1/5 W J C06001026P520	5		R240	METAL FILM	470 ohm 1/5 W J C06004716P520	1	
R516	CARBON FILM	4.7 kohm 1/5 W J C00004726P520	1		R241	CARBON FILM	70 kohm 1/5 W J C00001036P520	1	
R517/R518	METAL FILM	220 ohm 1/5 W J C06002216P520	2		R242	CARBON FILM	7.5 kohm 1/5 W J C00007526P520	1	D/RDS(Only)
R519	CARBON FILM	100 kohm 1/5 W J C00001046P520	1		R243	CARBON FILM	150 kohm 1/5 W J C00001546P520	1	
R522/R523	METAL FILM	220 ohm 1/5 W J C06002216P520	2		R244C/L/R	CARBON FILM	33 kohm 1/5 W J C00003336P520	3	
R524	METAL FILM	1 kohm 1/5 W J C06001026P520	1		R245C	METAL FILM	1.8 kohm 1/5 W J C06001826P520	1	
R525	CARBON FILM	100 kohm 1/5 W J C00001046P520	1		R245L/R	METAL FILM	1.2 kohm 1/5 W J C06001226P520	2	
					R246C	METAL FILM	1 kohm 1/5 W J C06001026P520	3	
					R247C/L/R	METAL FILM	47 ohm 1 W J C060047065520	3	
					R249C/L/R	METAL FILM	47 ohm 1 W J C060047065520	3	
					R251C/L/R	CARBON FILM	33 kohm 1/5 W J C00003336P520	3	
PCB3 ASSEMBLY P.C.BOARD AMP302					ASSEMBLY P.C.BOARD CNT-2				
CAPACITORS					CN206				
C201C/L/R	ELECTROLYTIC SG	47 uF 16 V M D040470083100	3		PLUG, 8P L111507600810 1				
C202C/L/R	CERAMIC TUBULAR	88 pF 50 V J D001680067530	3		CN212 PLUG, 8P L111507600810 1				
C203C/L/R	ELECTROLYTIC SG	100 uF 10 V M D040101082060	3						
C204C/L/R	ELECTROLYTIC SA	470 uF 6.3 V M D040471081100	3						
C205C/L/R	ELECTROLYTIC SG	10 uF 50 V M D040100087050	3						
C206C/L/R	CERAMIC TUBULAR	47 pF 50 V J D001470067530	3						
C207C/L/R	ELECTROLYTIC SG	4.7 uF 50 V M D0404R7087100	3						
C208C/L/R	CERAMIC TUBULAR	15 pF 50 V J D001150067530	3						
C209C/L/R	ELECTROLYTIC SM	47 uF 100 V M D04047008C130	3						
C210C/L/R	ELECTROLYTIC SM	47 uF 100 V M D04047008C130	3						
C211C/L/R	ELECTROLYTIC SG	22 uF 35 V M D040220085100	3						
C212L/R	MYLAR	0.047 uF 100 V J D02047306C060	2						
C213	ELECTROLYTIC SA	470 uF 6.3 V M D040471081100	3						
C214C/L/R	CERAMIC TUBULAR	470 pF 50 V D005471077530	3						
C215	ELECTROLYTIC SG	1 uF 50 V M D040010087050	1						
CONNECTORS					PCB4 ASSEMBLY P.C.BOARD AMP202				
CP201	PLUG, 8P	L101220090000	1		CAPACITORS				
CP202	PLUG, 4P	L101220040000	1		C201SL/SR	ELECTROLYTIC SG	47 uF 16 V M D040470083100	2	
CP204	PLUG, 3P	L102526703010	1		C202SL/SR	CERAMIC TUBULAR	100 pF 50 V J D001101077530	2	
CP205	PLUG, 3P	L104202003000	1		C203SL/SR	ELECTROLYTIC SG	100 uF 10 V M D040101082060	2	
CP408	PLUG, 2P	L101220020000	1		C204SL/SR	ELECTROLYTIC SG	47 uF 25 V M D040470084100	2	
CP206	PULG, 8P	L101507600800	1		C205SL/SR	ELECTROLYTIC SG	10 uF 50 V M D040100087050	2	
CP410	PLUG, 2P	L102526702010	1	D/RDS(Only)	C206SL/SR	CERAMIC TUBULAR	47 pF 50 V J D001470067530	2	
CN203	LEAD ASSY, 3P, 280mm	L022032634320	2		C207SL/SR	ELECTROLYTIC SG	4.7 uF 50 V M D0404R7087100	2	
CN411	LEAD ASSY, 3P, 120mm	L022031236320	1		C208L/R	CERAMIC TUBULAR	15 pF 50 V J D001150067530	2	
					C209SL/SR	ELECTROLYTIC SM	47 uF 100 V M D04047008C130	2	
					C210SL/SR	ELECTROLYTIC SM	47 uF 100 V M D04047008C130	2	
					C211SL/SR	ELECTROLYTIC SG	10 uF 50 V M D040100087050	2	
					C214SL/SR	CERAMIC TUBULAR	470 pF 50 V D005471077530	2	
					C224SL/SR	CERAMIC TUBULAR	47 pF 50 V J D001470067530	2	
					CONNECTORS				
					CP203	PULG, 3P	L101220030000	1	
					CP207	PULG, 7P	L104202000700	1	
					CP208	PULG, 8P	L104202000800	1	
					CP209	PULG, 3P	L101220020010	1	
					CP210	PULG, 3P	L104202000300	1	
					CP211	PULG, 3P	L101220030000	1	
					DIODES				
					D201SL/SR	1N4148, SWITCHING	K000414801520	2	
					D202SL/SR	1N4148, SWITCHING	K000414801520	2	
					L201SL/SR	INDUCTOR, 0.5 uH	D330900001320	2	
					TRANSISTORS				
					Q203SL/SR	KTA1268/KTA970, PNP	J5001268B0050	2	
					Q204SL/SR	KTA1268/KTA970, PNP	J5001268B0050	2	
					Q205SL/SR	KTA1268/KTA970, PNP	J5001268B0050	2	
					Q206SL/SR	BKTA1267Y, PNP	J5001267Y0050	2	
					Q207SL/SR	KTC3200/KTC2240BL, NPN	J5023200B0050	2	
					Q208SL/SR	KTC3200/KTC2240BL, NPN	J5023200B0050	2	
					25C3423		J5023423C0000	2	
					Q211SL/SR	2SA1360	J5001360C0000	2	
					Q212SL/SR	2SC4137, NPN	J5024137V0130	2	
					Q213SL/SR	2SC4883A, NPN	J5024883Y0000	2	
					Q214SL/SR	2SA1859, PNP	J5021859Y0000	2	
					Q215SL/SR	2SC3519A, NPN	J5023519Y0000	2	
					Q216SL/SR	2SA1386A, PNP	J5001386Y0000	2	
					Q217SL/SR	2SC1740S, NPN	J5021740S0010	2	
					RESISTORS				
					R201SL/SR	METAL FILM	1 kohm 1/5 W J C06001026P520	2	
					R203SL/SR	CARBON FILM	33 kohm 1/5 W J C00003336P520	2	
					R204SL/SR	CARBON FILM	10 kohm 1/5 W J C00001036P520	2	
					R205SL/SR	METAL FILM	270 ohm 1/5 W J C06002716P520	2	
					R206SL/SR	METAL FILM	390 ohm 1/5 W J C06003916P520	2	
					R207SL/SR	METAL FILM	390 ohm 1/5 W J C06003916P520	2	
					R208SL/SR	METAL FILM	1.5 kohm 1/5 W J C06001526P520	2	
					R209SL/SR	METAL FILM	1.5 kohm 1/5 W J C06001526P520	2	
					RESISTORS				
R201C/L/R	METAL FILM	1 kohm 1/5 W J C06001026P520	3						
R203C/L/R	CARBON FILM	33 kohm 1/5 W J C00003336P520	3						
R204C/L/R	CARBON FILM	10 kohm 1/5 W J C00001036P520	3						
R205C/L/R	METAL FILM	270 ohm 1/5 W J C06002716P520	3						

Ref. No.	Description	Part No.	Qty	Version	Ref. No.	Description	Part No.	Qty	Version
R210S/LR	METAL FILM	560 ohm 1/5 W J C06005616P520	2		R385	CARBON FILM	180 kohm 1/5 W J C00001848P520	1	
R211S/LR	METAL FILM	560 ohm 1/5 W J C06005616P520	2		R386	METAL FILM	3.9 kohm 1/5 W J C06003926P520	1	A(Only)
R212S/LR	METAL FILM	560 ohm 1/5 W J C06005616P520	2		R387/R388	METAL FILM	470 ohm 1/5 W J C06004716P520	2	
R213S/LR	METAL FILM	560 ohm 1/5 W J C06005616P520	2						
R214S/LR	METAL FILM	560 ohm 1/5 W J C06005616P520	2						
R217S/LR	METAL FILM	82 ohm 1/5 W J C06008206P520	2						
R218S/LR	METAL FILM	82 ohm 1/5 W J C06008206P520	2						
R219S/LR	METAL FILM	1 kohm 1/5 W J C06001226P520	2						
R220S/LR	METAL FILM	470 ohm 1/5 W J C06004716P520	2						
R222S/LR	CARBON FILM	22 kohm 1/5 W J C00002236P520	2						
R223S/LR	CARBON FILM	22 kohm 1/5 W J C00002236P520	2						
R224S/LR	METAL FILM	82 ohm 1/5 W J C06008206P520	2						
R225S/LR	METAL FILM	1 kohm 1 W J C060010265520	2						
R226S/LR	METAL FILM	1 kohm 1 W J C060010265520	2						
R227S/LR	CEMENT (Dual)	0.27 ohm 5 W J C141R27079300	2						
R228S/LR	METAL FILM	1 kohm 1/5 W J C06001026P520	2						
R229S/LR	METAL FILM	1 kohm 1/5 W J C06001026P520	2						
R230S/LR	METAL FILM	910 ohm 1/5 W J C06009116P520	2						
R231S/LR	CARBON FILM	6.8 kohm 1/5 W J C00006826P520	2						
R235S/LR	METAL FILM	10 ohm 1 W J C060010065520	2						
R238S/LR	CARBON FILM	22 kohm 1/5 W J C00002236P520	2						
R244S/LR	CARBON FILM	33 kohm 1/5 W J C00003336P520	2						
R245S/LR	METAL FILM	2.2 kohm 1/5 W J C06002226P520	2						
R246S/LR	METAL FILM	1 kohm 1/5 W J C06001026P520	2						
R247S/LR	METAL FILM	47 ohm 1 W J C060047065520	2						
R249S/LR	METAL FILM	47 ohm 1 W J C060047065520	2						
R251S/LR	CARBON FILM	33 kohm 1/5 W J C00003336P520	2						
* ASSEMBLY P.C.BOARD FRONT (PCB 5, 6, 7, 8)									
PCB5	ASSEMBLY P.C.BOARD FRONT								
	CAPACITORS								
C301-C310	CERAMIC TUBULAR	100 pF 50 V J D001101077530	10						
C312	MYLAR	0.047 μ F 100 V J D02047306C060	2						
C313	ELECTROLYTIC SG	0.1 μ F 50 V M D040R10087050	1						
C316/C317	CERAMIC TUBULAR	100 pF 50 V J D001101077530	2						
C318/C319	CERAMIC TUBULAR	820 pF 50 V J D005821077530	2						
C320	ELECTROLYTIC SG	47 μ F 16 V M D040470083100	1						
C321	ELECTROLYTIC SG	47 μ F 25 V M D040470084100	1						
C322	ELECTROLYTIC SG	0.047 μ F 5.5 V M D090473704010	1						
C323	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	1						
C324	ELECTROLYTIC SG	47 μ F 50 V M D040470087100	1						
C325	ELECTROLYTIC SG	10 μ F 35 V M D040100085100	1	A(Only)					
	CONNECTORS								
CN300	LEAD ASSY, 5P, 80mm	L022050834320	1		CN601	LEAD ASSY, 3P, 400mm	L022034071320	1	
CN301	PLUG, S2575-2130	L131525752100	1		CN602	LEAD ASSY, 6P, 200mm	L03206277320	1	
CN302	LEAD ASSY, 8P, 350mm	L022083534320	1						
CN303	LEAD ASSY, 12P, 200mm	L022122034320	1						
CP304	PLUG ANGLE, 2P,	L101220020010	1						
CNT301	CABLE FPC, 2P, 350mm	L301186213590	1						
	DIODES								
D301-D312	1N4148, SWITCHING	K000414801520	12						
D313	LED, SLR-34URCF25	K500032101120	1						
D314/D315	1N4148, SWITCHING	K000414801520	2						
	INTEGRATED CIRCUITS								
IC301	CXP82840-119Q	J089393227330	1						
IC302	CRV1G342-185BQ, REMOTE MODULE	E940342210000	1						
	TRANSISTORS								
Q301	BKTC3199/2SC3199Y, NPN	J5023199Y0050	1	A(Only)					
Q306-Q308	BKTC3199/2SC3199Y, NPN	J5023199Y0050	3						
Q309	MPSA06, NPN	J5020600Y0050	1						
Q310	DTC114YS, NPN	J6020114Y0050	1						
	RESISTORS								
R301-R310	METAL FILM	1 kohm 1/5 W J C06001026P520	10						
R312-R320	CARBON FILM	100 kohm 1/5 W J C00001046P520	9						
R321-R324	CARBON FILM	47 kohm 1/5 W J C00004736P520	4						
R325	CARBON FILM	22 kohm 1/5 W J C00002236P520	1						
R326-R328	CARBON FILM	10 kohm 1/5 W J C00001036P520	3						
R329	METAL FILM	4.7 kohm 1/5 W J C06004726P520	1						
R330/R331	CARBON FILM	22 kohm 1/5 W J C00002236P520	2						
R332/R333	CARBON FILM	10 kohm 1/5 W J C00001036P520	2						
R336/R337	CARBON FILM	10 kohm 1/5 W J C00001036P520	2						
R338	CARBON FILM	10 kohm 1/5 W J C00001036P520	1						
R339-R341	CARBON FILM	10 kohm 1/5 W J C00001036P520	3						
R342	CARBON FILM	100 kohm 1/5 W J C00001046P520	1						
R343/R344	CARBON FILM	10 kohm 1/5 W J C00001036P520	2						
R346-R349	CARBON FILM	100 kohm 1/5 W J C00001046P520	4						
R351/R352	METAL FILM	3.3 ohm 1/5 W J C0603R306P520	2						
R353-R355	CARBON FILM	10 kohm 1/5 W J C00001036P520	3						
R356	CARBON FILM	100 kohm 1/5 W J C00001046P520	1						
R357/R358	METAL FILM	100 ohm 1/5 W J C06001016P520	2						
R359/R360	CARBON FILM	100 kohm 1/5 W J C00001046P520	2						
R363	CARBON FILM	22 kohm 1/5 W J C00002236P520	1						
R364	CARBON FILM	220 kohm 1/5 W J C00002246P520	1						
R366-R368	METAL FILM	2.2 kohm 1/5 W J C06002226P520	3						
R369/R370	CARBON FILM	68 kohm 1/5 W J C00006836P520	2						
R372	CARBON FILM	10 kohm 1/5 W J C00001036P520	1	A/K(Only)					
R373/R374	CARBON FILM	100 kohm 1/5 W J C00001046P520	2	RDS(Only)					
R375	CARBON FILM	10 kohm 1/5 W J C00001036P520	1	A/K(Only)					
R376	METAL FILM	100 ohm 1/5 W J C06001016P520	1						
R377	CARBON FILM	100 kohm 1/5 W J C00001046P520	1						
R378	CARBON FILM	10 kohm 1/5 W J C00001036P520	1						
R379	METAL FILM	330 ohm 1/5 W J C06003316P520	1						
R380	METAL FILM	180 ohm 1/5 W J C06001816P520	1						
R381	CARBON FILM	10 kohm 1/5 W J C00001036P520	1						
R382	METAL FILM	1 kohm 1/5 W J C06001026P520	1	A(Only)					
R383/R384	CARBON FILM	10 kohm 1/5 W J C00001036P520	2	A(Only)					
	PCB6								
	ASSEMBLY P.C.BOARD TONE								
	CAPACITORS								
C601/LR	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	2						
C602/LR	CERAMIC TUBULAR	100 pF 50 V J D001101077530	2						
C603/LR	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	2						
C604/LR	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	2						
C605/LR	MYLAR	0.082 μ F 63 V K D020823078060	2						
C606/LR	MYLAR	0.015 μ F 100 V J D02015306C060	2						
C607/LR	MYLAR	0.022 μ F 100 V J D02022306C060	2						
C608/LR	MYLAR	0.0033 μ F 100 V J D02033206C060	2						
C609/LR	MYLAR	0.33 μ F 63 V K D020334078060	2						
C610/LR	MYLAR	0.0082 μ F 100 V J D02082206C060	2						
C611/LR	ELECTROLYTIC SG	1 μ F 50 V M D040109087050	2						
C614	ELECTROLYTIC SG	47 μ F 25 V M D04047084100	1						
C615	ELECTROLYTIC SG	3.3 μ F 50 V M D040339087050	1						
	CONNECTORS								
CN601	LEAD ASSY, 3P, 400mm	L022034071320	1						
CN602	LEAD ASSY, 6P, 200mm	L03206277320	1						
	INTEGRATED CIRCUIT								
IC601	NJM2068DD	J121455900000	1						
	TRANSISTORS								
Q601	BKTC3199/2SC3199Y, NPN	J5023199Y0050	1						
Q602	DTA114YS, PNP	J8000114Y0010	1						
Q603/LR	2SK117Y, FET	J5441170Y0050	2						
	RESISTORS								
R601/LR	CARBON FILM	100 kohm 1/5 W J C00001046P520	2						
R602/LR	CARBON FILM	1 Mohm 1/5 W J C00001056P520	2						
R603/LR	CARBON FILM	47 kohm 1/5 W J C00004736P520	2						
R604/LR	METAL FILM	2.7 kohm 1/5 W J C06002726P520	2						
R605/LR	CARBON FILM	10 Mohm 1/5 W J C00001066P520	2						
R606/LR	METAL FILM	4.7 kohm 1/5 W J C06004726P520	2						
R607/LR	CARBON FILM	27 kohm 1/5 W J C00002736P520	2						
R608/LR	METAL FILM	3.3 kohm 1/5 W J C06003326P520	2						
R609/LR	CARBON FILM	22 kohm 1/5 W J C00002236P520	2						
R610/LR	METAL FILM	560 ohm 1/5 W J C06005616P520	2						
R611/LR	METAL FILM	2.2 kohm 1/5 W J C06002226P520	2						
R612/LR	METAL FILM	1 kohm 1/5 W J C06001026P520	2						
R613/LR	CARBON FILM	100 kohm 1/5 W J C00001046P520	2						
R614	CARBON FILM	100 kohm 1/5 W J C00001046P520	1						
R615	CARBON FILM	1 Mohm 1/5 W J C00001056P520	1						
R616/R617	METAL FILM	220 ohm 1/5 W J C06002216P520	2						
R618/LR	CARBON FILM	1 Mohm 1/5 W J C00001056P520	2						
	SEMI FIXED VARIABLE RESISTORS								
VR601/VR602	RK14K1260A07, 100K(C)	C450042060000	2						
VR603	RK11K1160A07, 100KW	C450042050000	1						
	PCB7								
	ASSEMBLY P.C.BOARD SPKR SWITCH								
C701/LR	CERAMIC TUBULAR	560 pF 50 V J D005581077530	2						
R701/LR	METAL FILM	470 ohm 2 W J C060047166520	2						
SW701/SW702	SWITCH PUSH	G000041170000	2						
	PCB8								
C751-C755	CERAMIC TUBULAR	100 pF 50 V J D001101077530	5						
C757/C758	CERAMIC TUBULAR	0.1 μ F 50 V J D005104097530	2						
CP300	PLUG ANGLE, 5P	L010122005001	1						
CN752	LEAD ASSY, 5P, 350mm	L022053534320	1						

Ref. No.	Description	Part No.	Qty	Version	Ref. No.	Description	Part No.	Qty	Version
C467	CERAMIC DISC	0.0047 μ F 100 V Z D004472097080	1		C805/C806	ELECTROLYTIC SG	47 μ F 25 V M D040470084100	2	
L201C	COIL INDUCTOR, 0.5 μ H	D330900001320	1		C807	ELECTROLYTIC SG	1 μ F 50 V M D040010087050	1	
CN204	CONNECTORS				C808	CERAMIC TUBULAR	0.001 μ F 50 V K D005102077530	1	
CN205	LEAD ASSY, 3P, 100mm	L021031034310	1		C809	ELECTROLYTIC SG	22 μ F 16 V M D040220083100	1	
CN210	LEAD ASSY, 8P, 240mm	L020082441660	1		C810	ELECTROLYTIC SG	1 μ F 50 V M D040010087050	1	
CP452	LEAD ASSY, 3P, 300mm	L020033041660	1		C811	CERAMIC TUBULAR	0.001 μ F 50 V K D005102077530	1	
	PULG, 4P	L104202000400	1		C812	ELECTROLYTIC SG	10 μ F 35 V M D040100085100	1	
	RESISTORS				C813-C816	ELECTROLYTIC SG	47 μ F 25 V M D040470084100	4	
R235C	METAL FILM	10 ohm 1 W J C060010065520	1		C817	CERAMIC TUBULAR	0.1 μ F 50 V K D005103077530	1	
R451-R453	METAL FILM	10 ohm 1 W J C060010065520	3		C818-C820	CERAMIC TUBULAR	100 pF 50 V J D001101077530	3	
PCB10	ASSEMBLY P.C. BOARD SUPPLY				C821-C823	MYLAR	0.1 μ F 63 V K D020104078060	3	
	CAPACITORS				C824	CERAMIC TUBULAR	680 pF 50 V D005681077530	1	
C400	MYLAR	0.1 μ F 250 V M D02010408H210	1		C825	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	1	
C401	CERAMIC DISC	0.0047 μ F 400 V D00847208K010	1		C826	MYLAR	0.1 μ F 63 V K D020104078060	1	
C402	ELECTROLYTIC SG	1000 μ F 16 V M D040102083200	1		C827	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	1	
C403/C404	MYLAR	0.047 μ F 100 V J D02047306C060	2		C828/C829	MYLAR	0.22 μ F 63 V K D020224078060	2	
C405	ELECTROLYTIC SG	100 μ F 50 V M D040101087100	1		C830-C833	MYLAR	0.33 μ F 63 V K D020334078060	4	
C406	ELECTROLYTIC SG	1 μ F 50 V M D040010087050	1		C834-C837	MYLAR	0.022 μ F 100 V J D02022306C060	4	
C407	CERAMIC TUBULAR	0.1 μ F 50 V D005104097530	1		C838	MYLAR	0.15 μ F 63 V K D020154078060	1	
C408	ELECTROLYTIC SG	1 μ F 50 V M D040010087050	1		C839	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	1	
	CONNECTORS				C840/C841	MYLAR	0.22 μ F 63 V K D020224078060	2	
CP400	AC PLUG	L104020040000	1		C842	ELECTROLYTIC SG	10 μ F 50 V M D040010087050	1	
CP751	PLUG, BL102R	L033588502400	1		C843-C845	MYLAR	0.01 μ F 100 V J D02010306C060	3	
CP401	PLUG, 2P	L108202000220	1		C846	ELECTROLYTIC SG	100 μ F 10 V M D040101082060	1	
CP402	PLUG, 4P	L102526704010	1		C847	MYLAR	0.1 μ F 63 V K D020104078060	1	
CP302	PLUG, 8P	L101220080000	1		C848/LR	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	2	
	DIODES				C849-C851	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	3	
D401-D407	RECTIFIER, 1N4003	K040400300520	7		C852/C853	ELECTROLYTIC SG	47 μ F 25 V M D040470084100	2	
D408	ZENER, UZ 9.1V BSC	K06009R124520	1		C854	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	1	
D409	ZENER, UZ 7.5V BSB	K06007R524520	1		C855/C856	ELECTROLYTIC SG	47 μ F 25 V M D040470084100	2	
D410	ZENER, UZ 9.1V BSC	K06009R124520	1		C857	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	1	
D411	ZENER, UZ 12V BSC	K060120024520	1		C858/C859	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	2	
D412	ZENER, UZ 4.3V BSA	K06004R314520	1		C860	ELECTROLYTIC SG	1 μ F 50 V M D040010087050	1	
	FUSES				C861	CERAMIC TUBULAR	0.001 μ F 50 V K D005102077530	1	
F400	S.B 6A/125V	G650602121150	1	A	C862	ELECTROLYTIC SG	22 μ F 18 V M D040220083100	1	
F400	T4A/250V	G650402251160	1	D/RDS	C863	ELECTROLYTIC SG	1 μ F 50 V M D040010087050	1	
F401	T2A/250V	G650202251160	1	D/RDS	C864	CERAMIC TUBULAR	0.001 μ F 50 V K D005102077530	1	
F402	NB350mA/125V	G650351121160	1	A	C865	ELECTROLYTIC SG	0.47 μ F 50 V M D04047087100	1	
F402	T50mA	G650501251160	1	D/RDS	C866	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	1	
	RESISTORS				C867	CERAMIC TUBULAR	680 pF 50 V D005681077530	1	
R401	METAL FILM	10 ohm 1 W J C060010065520	1		C868	MYLAR	0.0056 μ F 100 V J D02056206C060	1	
R402	METAL FILM	470 ohm 1/5 W J C06004716P520	1		C869	MYLAR	0.0047 μ F 100 V J D02047206C060	1	
R403	CARBON FILM	10 kohm 1/5 W J C00001036P520	1		C870	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	1	
R404	METAL FILM	330 ohm 1/5 W J C06003316P520	1		C871	CERAMIC TUBULAR	470 pF 50 V D005471077530	1	
R405	CARBON FILM	15 kohm 1/5 W J C00001536P520	1		C872	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	1	
R406	METAL FILM	3.3 Mohm 1/2 W J C06003356P520	1		C873	ELECTROLYTIC SG	1 μ F 50 V M D040010087050	1	
R407	METAL FILM	2.2 kohm 1/5 W J C06002226P520	1		C874	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	1	
R408	METAL FILM	56 ohm 1 W J C060056085520	1		C875	MYLAR	0.022 μ F 100 V J D02022306C060	1	
	MISCELLANEOUS				C876	MYLAR	0.0047 μ F 100 V J D02047206C060	1	
IC400	GD7806	J126780600000	1		C877	MYLAR	0.0039 μ F 100 V J D02039206C060	1	
Q400	2SC1740S, NPN	J502174050010	1		C878	MYLAR	0.068 μ F 63 V K D020683078060	1	
RLY400	HRCR313DC12V	G680121630000	1		C879	MYLAR	0.22 μ F 63 V K D020224078060	1	
PCB11	ASSEMBLY P.C. BOARD PRE IN/OUT				C880	MYLAR	0.1 μ F 63 V K D020104078060	1	
	CAPACITORS				C881	ELECTROLYTIC SG	220 μ F 10 V M D040221082100	1	
C651-C658	CERAMIC TUBULAR	100 pF 50 V J D001101077530	8		C882	ELECTROLYTIC SG	220 μ F 16 V M D040221083100	1	
CN654	LEAD ASSY, 7P, 120mm	L022071234320	1		C883	ELECTROLYTIC SG	220 μ F 10 V M D040221082100	1	
CP601	PLUG, 3P	L101220030000	1		C884/C885	MYLAR	0.1 μ F 63 V K D020104078060	2	
CP602	PLUG, 6P	L101220060000	1		C886-C888	CERAMIC TUBULAR	100 pF 50 V J D001101077530	3	
CP654	LEAD ASSY, 9P, 240mm	L022092434320	1		C889/C890	ELECTROLYTIC SG	220 μ F 16 V M D040221083100	2	
CN209	LEAD ASSY, 3P, 450mm	L022034537320	1		C891	CERAMIC TUBULAR	150 pF 50 V D005151077530	1	
	DIODES				C892	MYLAR	0.022 μ F 100 V J D02022306C060	1	
D652-D654	1N4148, SWITCHING	K000414801520	3		C893	CERAMIC DISC	680 pF 50 V J D022881067050	1	
	TRANSISTORS				C894	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	1	
Q651	KTD1303, NPN	J503130300050	1		C895	ELECTROLYTIC SG	470 μ F 10 V M D040471082100	1	
Q653-Q658	KTD1303, NPN	J503130300050	4		C896	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	1	
Q658-Q660	DTA114YS, PNP	J600011470010	3		C897	CERAMIC DISC	680 pF 50 V M D022881067050	1	
	RESISTORS				C898	MYLAR	0.022 μ F 100 V J D02022306C060	1	
R651/R652	METAL FILM	470 ohm 1/5 W J C06004716P520	2		C899	CERAMIC TUBULAR	150 pF 50 V D005151077530	1	
R653	METAL FILM	1 kohm 1/5 W J C06001026P520	1		C900	MYLAR	0.15 μ F 63 V K D020154078060	1	
R654/R655	METAL FILM	2.2 kohm 1/5 W J C06002226P520	2		C901-C903	CERAMIC TUBULAR	100 pF 50 V J D001101077530	3	
R656/R657	METAL FILM	1 kohm 1/5 W J C06001026P520	1		C904/C905	ELECTROLYTIC SG	47 μ F 25 V M D040470084100	2	
R658/R659	METAL FILM	2.2 kohm 1/5 W J C06002226P520	2		C906	ELECTROLYTIC SG	1 μ F 50 V M D040010087050	1	
R660/R661	METAL FILM	1 kohm 1/5 W J C06001026P520	2		C907	MYLAR	0.01 μ F 100 V J D02010306C060	1	
R662	METAL FILM	2.2 kohm 1/5 W J C06002226P520	1		C908/C909	ELECTROLYTIC SG	47 μ F 25 V M D040470084100	2	
R663	METAL FILM	1 kohm 1/5 W J C06001026P520	1		C910-C912	CERAMIC TUBULAR	100 pF 50 V J D001101077530	4	
R664	METAL FILM	2.2 kohm 1/5 W J C06002226P520	1		C913	ELECTROLYTIC SG	100 μ F 16 V M D040101083100	1	
R665/R668	METAL FILM	1 kohm 1/5 W J C06001026P520	1		C914/C915	ELECTROLYTIC SG	100 μ F 10 V M D040101082060	2	
R667	METAL FILM	470 ohm 1/5 W J C06004716P520	1		C916	MYLAR	0.047 μ F 100 V J D02047306C060	1	
R670-R672	CARBON FILM	47 kohm 1/5 W J C00004736P520	3		C917	ELECTROLYTIC SG	10 μ F 50 V M D040100087050	1	
	CONNECTORS				C918/C919	ELECTROLYTIC SG	220 μ F 10 V M D040221082100	2	
PCB12	ASSEMBLY P.C. BOARD SURROUND				C920	CERAMIC TUBULAR	680 pF 50 V D005681077530	1	
	CAPACITORS				C921/C922	CERAMIC TUBULAR	0.1 μ F 50 V D005104097530	2	
C801/LR	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	2		C924-C926	CERAMIC TUBULAR	0.1 μ F 50 V D005104097530	3	
C802/LR	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	2						
C804/LR	ELECTROLYTIC SG	4.7 μ F 50 V M D04047087100	2						
	CONNECTORS								
	PLUG, 8P	L115075008010	1						
	PLUG, 12P	L101220120000	1						
	PLUG, 6P	L101220060000	1						
	PLUG, 7P	L101220070000	1						
	DIODES								
	1N4148, SWITCHING	K000414801520	2						
	ZENER, UZ 12V BSC	K060120024520	1						
	1N4148, SWITCHING	K000414801520	2						
	ZENER, UZ 6.8V BSC	K06006R814520	2						
	INTEGRATED CIRCUIT								
	KIA4559P/KIA75559P	J121455900010	5						
	MC14094BCP	J040140940000	1						
	SSM-2126	J081212600000	1						
	LV-1000	J089100000010	1						
	256K D-RAM	J001612560000	1						

Ref. No.	Description	Part No.	Q'ty	Version	Ref. No.	Description	Part No.	Q'ty	Version
IC810	MC14094BCP	J040140940000	1		PCB1	ASSEMBLY P.C.BOARD TUNER	7028040776500		A
IC811	LC7822	J080782200000	1		PCB1	ASSEMBLY P.C.BOARD TUNER	7028040789000		D
IC812	TC9299	J084929900000	1		PCB1	ASSEMBLY P.C.BOARD TUNER	7028040770600		K
IC813	TA7291S	J127729100000	1		PCB1	ASSEMBLY P.C.BOARD TUNER	7028040790800		RDS
TRANSISTORS									
Q801	BKTA1267Y, PNP	J5001267Y0050	1		PCB2	ASSEMBLY P.C.BOARD MAIN	7028040775000		A
Q802-Q804	DTC114YS, NPN	J6020114Y0050	3		PCB2	ASSEMBLY P.C.BOARD MAIN	7028040787500		D
Q805	DTA114YS, PNP	J6000114Y0010	1		PCB2	ASSEMBLY P.C.BOARD MAIN	7028040769100		K
Q806	BKTC3199/2SC3199Y, NPN	J5023199Y0050	1		PCB2	ASSEMBLY P.C.BOARD MAIN	7028040789300		RDS
RESISTORS									
R801/L/R	CARBON FILM	100 kohm 1/5 W J C00001046P520	2		PCB3	ASSEMBLY P.C.BOARD AMP302	7028040776400		A
R802	CARBON FILM	22 kohm 1/5 W J C00002236P520	1		PCB3	ASSEMBLY P.C.BOARD AMP302	7028040788900		D
R803/L/R	CARBON FILM	100 kohm 1/5 W J C00001046P520	2		PCB3	ASSEMBLY P.C.BOARD AMP302	7028040770500		K
R804/L/R	METAL FILM	470 ohm 1/5 W J C06004716P520	2		PCB3	ASSEMBLY P.C.BOARD AMP302	7028040790700		RDS
R805/L/R	METAL FILM	1 kohm 1/5 W J C06001026P520	2		▶ THE ASS'Y PCB AMP302(PCB3) INCLUDE BELOW.				
R806/L/R	CARBON FILM	100 kohm 1/5 W J C00001046P520	2		① THE ASS'Y PCB CNT-2.				
R807/R808	METAL FILM	220 ohm 1/5 W J C06002216P520	2		PCB4	ASSEMBLY P.C.BOARD AMP202	7028040776700		A
R809	METAL FILM	1 kohm 1/5 W J C06001026P520	1		PCB4	ASSEMBLY P.C.BOARD AMP202	7028040789200		D
R810	CARBON FILM	1 Mohm 1/5 W J C00001056P520	1		PCB4	ASSEMBLY P.C.BOARD AMP202	7028040770800		K
R811	METAL FILM	1.5 kohm 1/5 W J C06001526P520	1		PCB4	ASSEMBLY P.C.BOARD AMP202	7028040791000		RDS
R812	CARBON FILM	5.1 kohm 1/5 W J C00005126P520	1		PCB5	ASSEMBLY P.C.BOARD FRONT	7028040775200		A
R813	CARBON FILM	10 kohm 1/5 W J C00001036P520	1		PCB5	ASSEMBLY P.C.BOARD FRONT	7028040787700		D
R814	METAL FILM	1 kohm 1/5 W J C06001026P520	1		PCB5	ASSEMBLY P.C.BOARD FRONT	7028040769300		K
R815	CARBON FILM	1 Mohm 1/5 W J C00001056P520	1		PCB5	ASSEMBLY P.C.BOARD FRONT	7028040789500		RDS
R816	METAL FILM	4.7 kohm 1/5 W J C06004726P520	1		▶ THE ASS'Y PCB FRONT(PCB5) INCLUDE BELOW.				
R817	METAL FILM	1.5 kohm 1/5 W J C06001526P520	1		① THE ASS'Y PCB TONE (PCB6).				
R818	CARBON FILM	10 kohm 1/5 W J C00001036P520	1		② THE ASS'Y PCB SPKER SWITCH (PCB7).				
R819	METAL FILM	1 kohm 1/5 W J C06001026P520	1		③ THE ASS'Y PCB VCR2 FRONT (PCB8).				
R820-R823	METAL FILM	220 ohm 1/5 W J C06002216P520	4		④ THE ASS'Y PCB SWITCH1.				
R824-R826	METAL FILM	1 kohm 1/5 W J C06001026P520	3		⑤ THE ASS'Y PCB SWITCH2.				
R827/R828	CARBON FILM	7.5 kohm 1/5 W J C00007526P520	2		PCB9	ASSEMBLY P.C.BOARD SUPPLY	7028040775900		A
R829	CARBON FILM	47 kohm 1/5 W J C00004736P520	1		PCB9	ASSEMBLY P.C.BOARD SUPPLY	7028040788400		D
R830	CARBON FILM	15 kohm 1/5 W J C00001536P520	1		PCB9	ASSEMBLY P.C.BOARD SUPPLY	7028040770000		K
R831	CARBON FILM	47 kohm 1/5 W J C00004736P520	1		PCB9	ASSEMBLY P.C.BOARD SUPPLY	7028040790200		RDS
R832	CARBON FILM	15 kohm 1/5 W J C00001536P520	1		▶ THE ASS'Y PCB SUPPLY (PCB10) INCLUDE BELOW.				
R833	CARBON FILM	10 Mohm 1/5 W J C00001066P520	1		① THE ASS'Y PCB SPEAKER (PCB9).				
R834-R836	CARBON FILM	22 kohm 1/5 W J C00002236P520	3		② THE ASS'Y PCB PRE IN/OUT (PCB11).				
R837/L/R	CARBON FILM	6.8 kohm 1/5 W J C00006826P520	2		③ THE ASS'Y PCB SURROUND (PCB12).				
R838/L/R	CARBON FILM	100 kohm 1/5 W J C00001046P520	2						
R839/R840	CARBON FILM	10 kohm 1/5 W J C00001036P520	2						
R841-R843	CARBON FILM	22 kohm 1/5 W J C00002236P520	3						
R844	METAL FILM	1.5 kohm 1/5 W J C06001526P520	1						
R845	METAL FILM	680 ohm 1/5 W J C06006816P520	1						
R846	METAL FILM	1.8 kohm 1/5 W J C06001826P520	1						
R847/R848	METAL FILM	220 ohm 1/5 W J C06002216P520	2						
R849/R850	CARBON FILM	22 kohm 1/5 W J C00002236P520	2						
R851/R852	METAL FILM	220 ohm 1/5 W J C06002216P520	2						
R854/R855	CARBON FILM	100 kohm 1/5 W J C00001046P520	2						
R856	CARBON FILM	47 kohm 1/5 W J C00004736P520	1						
R857/R858	CARBON FILM	100 kohm 1/5 W J C00001046P520	2						
R859	METAL FILM	1 kohm 1/5 W J C06001026P520	1						
R860	CARBON FILM	1 Mohm 1/5 W J C00001056P520	1						
R861	METAL FILM	1.5 kohm 1/5 W J C06001526P520	1						
R862	METAL FILM	3.3 kohm 1/5 W J C06003326P520	1						
R863	CARBON FILM	10 kohm 1/5 W J C00001036P520	1						
R864	METAL FILM	1 kohm 1/5 W J C06001026P520	1						
R865	CARBON FILM	1 Mohm 1/5 W J C00001056P520	1						
R866	METAL FILM	1.5 kohm 1/5 W J C06001526P520	1						
R867	METAL FILM	4.7 kohm 1/5 W J C06004726P520	1						
R868	CARBON FILM	10 kohm 1/5 W J C00001036P520	1						
R869	METAL FILM	1 kohm 1/5 W J C06001026P520	1						
R870	METAL FILM	3.9 kohm 1/5 W J C06003926P520	1						
R871	CARBON FILM	39 kohm 1/5 W J C00003936P520	1						
R872/R873	CARBON FILM	6.2 kohm 1/5 W J C00006226P520	2						
R874	CARBON FILM	15 kohm 1/5 W J C00001536P520	1						
R875	METAL FILM	3.3 kohm 1/5 W J C06003326P520	1						
R876	CARBON FILM	47 kohm 1/5 W J C00004736P520	1						
R877	CARBON FILM	1 Mohm 1/5 W J C00001056P520	1						
R878	METAL FILM	56 ohm 1/5 W J C06005606P520	1						
R879	CARBON FILM	10 kohm 1/5 W J C00001036P520	1						
R880	METAL FILM	56 ohm 1 W J C06005606P520	1						
R881	CARBON FILM	5.6 kohm 1/5 W J C00005626P520	1						
R882	CARBON FILM	47 kohm 1/5 W J C00004736P520	1						
R883-R885	METAL FILM	1 kohm 1/5 W J C06001026P520	3						
R886/R887	CARBON FILM	220 kohm 1/5 W J C00002246P520	2						
R888	METAL FILM	1 kohm 1/5 W J C06001026P520	1						
R889	CARBON FILM	47 kohm 1/5 W J C00004736P520	1						
R890	METAL FILM	220 ohm 1/5 W J C06002216P520	1						
R891-R893	METAL FILM	1 kohm 1/5 W J C06001026P520	3						
R894	CARBON FILM	100 kohm 1/5 W J C00001046P520	1						
R895-R897	METAL FILM	220 ohm 1/5 W J C06002216P520	3						
R898-R900	METAL FILM	1 kohm 1/5 W J C06001026P520	3						
R901	METAL FILM	820 ohm 1/5 W J C06008216P520	1						
R902	METAL FILM	220 ohm 1/5 W J C06002216P520	1						
R903	CARBON FILM	7.5 kohm 1/5 W J C00007526P520	1						
R904	CARBON FILM	10 kohm 1/5 W J C00001036P520	1						
R905	CARBON FILM	2.2 kohm 1/5 W J C00002226P520	1						
R906/R907	METAL FILM	150 ohm 1 W J C06001516P520	2						
R908	CARBON FILM	8.2 kohm 1/5 W J C00008226P520	1						
R909	CARBON FILM	100 kohm 1/5 W J C00001046P520	1						
R910	METAL FILM	2.2 kohm 1/5 W J C06002226P520	1						
SEMI FIXED VARIABLE RESISTORS									
VR801	50KAX4	C495145303200	1						
VR802	10K(B)	C541103115000	1						
MISCELLANEOUS									
X-TAL801	CST8M	E830800000050	1						

* Parts without Parts No are not supplied.

* Parts with blank version are available in common.

PRODUCT SAFETY NOTICE

Products marked with Δ have special characteristics important to safety. If you replace any of these components, read carefully the product safety notice in this manual. Don't degrade the safety of the product through improper servicing. Resistor/Capacitor tolerance - D : ($\pm 0.5\%$), J : ($\pm 5\%$), K : ($\pm 10\%$), M : ($\pm 20\%$), Z : (+80, - 20%)

* Parts without Parts No are not supplied.

* Parts with blank version are available in common.


PRODUCT SAFETY NOTICE

Products marked with Δ have special characteristics important to safety. If you replace any of these components, read carefully the product safety notice in this manual. Don't degrade the safety of the product through improper servicing. Resistor/Capacitor tolerance - D : ($\pm 0.5\%$), J : ($\pm 5\%$), K : ($\pm 10\%$), M : ($\pm 20\%$), Z : ($+80, -20\%$)


IC FUNCTIONAL BLOCK DIAGRAM

Model No. : R-725/RDS · AV-725


IC 1 : LM7001M




IC 3 : LA3401




IC 5 : LC7073M




IC 2 : LA1266G




IC 4 : TDA7330BD




IC 101, 107, 501, 503 : KIA4559




IC 104 : BA7625




IC 108, 400 : KA7806/GD7806
IC 109 : GD7815




IC 502, 812 : TC9299




IC 807 : SSM-2126




IC 106, 806, 810 : MC14094BCP




IC 102, 103 : LC7821




IC 811 : LC7822




IC 808 : LV-1000




IC 813 : TA7291S



IC 601 : NJM2068DD




IC 801-805 : KIA 4559P




BLOCK DIAGRAM

Model No. : R-725/RDS · AV-725




WIRING DIAGRAM

Model No. : R-725/RDS · AV-725



Model No. : R-725/RDS · AV-725




NOTES

1. Resistor values are indicated in ohms unless otherwise specified
(K=1.000 M=1.000.000)
2. Capacitor values are indicated in microfarads unless otherwise specified.
[p=micro-microfarads]



CAUTION

Safety precaution to be followed during servicing


- 1) Since those parts marked with  are critical parts for safety, use only the one described in the parts list.
- 2) Before returning the set to the customer make appropriate leakage current or resistance measurements to determine the exposed parts are properly insulated from the supply circuit.

SCHEMATIC DIAGRAM (II)


Model No. : R-725/RDS · AV-725




LV1000A




SSM-2126




LA3401





TA7291S
KIA4559



LC7073	BA7625
MC14053	TC9299
	MC14094



LC7821

LM7001/M
TDA7330BD

NOTES

1. Resistor values are indicated in ohms unless otherwise specified
[K=1.000 M=1.000.000]
2. Capacitor values are indicated in microfarads unless otherwise specified.
[p=micro-microfarads]

CAUTION

Safety precaution to be followed during servicing


1. Since those parts marked with a triangle are for safety, use only the one described in the parts list
2. Before returning the set to the customer make appropriate leakage or resistance measurements to determine the exposed parts are properly insulated from the supply circuit

	F101, F102
USA, CANADA	NB 1A 125V
EUROPE	T 1A 250V
KOREA, ETC	NB 1A 250V


SCHEMATIC DIAGRAM (III)

Model No. : R-725/RDS · AV-725


PCB3 (AMP 302)




CNT-2 B'D




KIA4559P
NJM2068D




CXP82840




KIA7806/GD7806
KIA7815/KIA7915
2SA1859A/2SC4883A




ZENER DIODE
IN4003
IN4148



2SA1215, 2SC2921




2SA1360 2SC3423
2SC4137




SCHEMATIC DIAGRAM (IV)

Model No. : R-725/RDS · AV-725


PCB4 (AMP 202)




KDA970/KTA1268
KTA1266/KTA1015Y
KTC2240/KTC3200
KTC3198/KTC1815Y




KRA107M/DTA114YS
DTC114YS KTD1303
KTC3199Y KTA1267
2SC1740



MPSA06
MPSA56




2SA1386Y
2SC3519Y




SCHEMATIC DIAGRAM (V)

PCB5 (FRONT)




PCB6 (TONE)




Model No. : R-725/RDS · AV-725


SW-1 B'D




SW-2 B'D



PCB7 (SPK S/W)




PCB8 (VCR2 FRONT)




SCHEMATIC DIAGRAM (VI)

Model No. : R-725/RDS · AV-725


PCB12 (SURROUND)



PCB9 (SPK TERMINAL)



PCB10 (SUPPLY)



	F 400	F 402
USA, CANADA	NS 350mA 125V	SB 10A 250V
EUROPE	T 500mA 250V	T 6A 250V
KOREA, ETC.	NS 500mA 250V	NS 6A 250V

PCB11 (PRE IN/OUT)

